



Autonomous driving Machine learning



Industrial

Informatics

Department

CIIRC

3


Prague


High-Performance Real-time Architectures for Low-Power Embedded Systems


HERCULES industrial and academic consortium aims to establish reference architectures and platforms for customized low-power heterogeneous computing systems delivering high performance functionality under real-time constraints across two main application domains (Automotive & Avionics).

HERCULES Main Goals:

- G1. Demonstrate and implement the first industrial-grade framework to provide real-time guarantees on top of cutting-edge heterogeneous COTS platforms for the embedded domain.
- G2. Obtain an order-of-magnitude improvement in the energy efficiency and cost of next generation real-time systems.
- G3. Provide a homogeneous programming interface to simplify the development of future real-time application on top of heterogeneous COTS platforms.







HERCULES will contribute to solve many present constrains of Advanced driving assistant systems (ADAS):

- Low-power budgets
- Space constrained
 - Move to embedded platforms
- Tight interaction with environment
- Hard Real-Time constraints
 - Still, poor research in this field























Formula 1/10th 1/10th the scale 10 times the fun

Scaled down model for experiments

- **Ubuntu and Robot Operating** System (ROS) on NVIDIA Jetson TX2
- sensors: LiDAR, Inertial unit
- actuators: servo and moment controlled 3-phase Brushless DC motor





ndustrial

Informatics

Department

CIIRC

CTU

글.

Prague

Our experiments:

- Trajectory planning
- **Indoor GPS**
- Sensor/data fusion
- **Dynamics and MPC**

Formula 1/10 Autonomous Racing Competition Our team won at the CPS Week, Porto April 2018



Our team: Jan Bednář, Jaroslav Klapálek, David Kopecký, Anders Solberg Pedersen, Joel Matějka, Martin Vajnar

Organizers:

University of Pennsilvania, **USA**

Industrial

Informatics

Department

CIIRC

5

- University of Virginia, USA
- University of Modena, Italy



Autonomous Car Slalom with Porsche Panamera



ndustrial

Informatics

Department

CIIRC


3

Prague




- DGPS, Camera, Lidar, car sensors (via FlexRay)
- **NVIDIA TX2 with ROS**
- Cone detection by camera
 - Color filtration
 - Contours detection
 - Triples detection + ROI setup
 - Creating feature vect. with HOG descr.
 - SVM clasification
- Data fusion
- Trajectory planning
- Trajectory following, lateral & longitudinal control

Hardware and Sensors



Hardware and Sensors - Parameters

- Camera Basler ace
 - 1920x1200 px, 40 fps, widescreen lens, USB 3.0
 - Manual color and brightnes settings
 - Fish-eye distortion
- Lidar Velodyne VLP-16
 - 16 layers, rotation range 5-20 Hz
 - Range: +-15 deg vertical, 360 deg horizontal, 100 m
 - Doesn't work with shiny surfaces (e.g. wet road)
- DGPS Trimble BX982
 - All positioning systems (GPS, GLONASS, GALILEO, ...)
 - 50 Hz output, correction inputs (RTCM)
 - Real accuracy 10 cm (cca 95% of time, depending on signal)
 - Very imprecise heading measurement
- Vector VN8900
 - FlexRay and CAN interfaces
 - CANoe, CANape support
 - Intel Core-i7 processor
- **NVIDIA TX2**
 - ARM cores: 2x Denver + 4x cortex A57
 - 256 cores in GPU



ndustrial


Informatics

Department

CIIRC

3

Prague



Cone Detection by Camera

- HOG Feature Descriptor

HOG (Histogram of Oriented Gradients) feature descriptor


 object appearance and shape within an image can be described by the distribution of intensity gradients or edge directions Informatics

Department

CIIRC

Prague

• the concatenation of histograms is represented as vector of numbers




Kalman Filter to Derive Possition and Heading

- Extended Kalman filter uses system dynamic model
 - Input: GPS position 50 Hz, car data (speed, angular speed)

ndustrial

Informatics

- Output: Car x,y position and heading
- to initialize heading it is needed to move the car and collect several GPS samples Optimal state estimate




Trajectory Planner

Goal: plan optimal trajectory with respect to car kinematics

we formulate the optimization problem (similar to LQ control):
minimize the cost function along the trajectory

$$\begin{aligned} & \underset{\mathbf{x}_1...\mathbf{x}_N, \mathbf{u}_0...\mathbf{u}_{N-1}}{\text{minimize}} & \sum_k (q_k x_k^2 + r_k u_k^2) \\ & \text{subject to} & \mathbf{x}_{k+1} = \mathbf{f}(\mathbf{x}_k, \mathbf{u}_k), \ k = 0, \dots, N-1 \\ & \mathbf{x}_N = \mathbf{x}_f \end{aligned}$$

Bicycle kinematics model



steering angle

 ${f v}$ - velocity vector

 β - slip angle between velocity vector and longitudinal direction

R - radius of car movement curve